

## **Data Sheet RSM-Ex 01**

## Remote Speaker Microphone for Zone 1/21



**ATEX** 



© II 2G Ex ib IIC T4 Gb © II 2D Ex ib IIIC T135°C Db IP64



© I M2 Ex ib I Mb

Technical Data				
Loudspeaker performance	Up to 103 dB			
Power supply	Li-lon 2200 mAh			
Charging	<ul> <li>Charging cable and docking station with magnetic charging plug: similar concept to Smart-Ex® 01 or Ident-Ex® 01.         A docking station without any electronics and a mounting option for the charging plug.     </li> <li>Optical charging level indication (multiple LEDs)</li> </ul>			
Plug	<ul> <li>3.5 mm 4-pin headset jack with locking mechanism for Smart-Ex® 01 /201 and Ex-Handy 09 / 209 versions</li> <li>3.5 mm 4-pin headset jack with locking mechanism for ecom Next Generation Phones (Ex-Handy 10; Smart-Ex® 02)</li> <li>3.5 mm 4-pin headset jack for Standard Android and Windows devices</li> </ul>			
Buttons	<ul> <li>PTT button operable with thick gloves</li> <li>Front facing multi-function button</li> <li>Volume up / down</li> <li>SOS button (optional)</li> </ul>			
Features	<ul> <li>Lone Worker Ready (optional SOS button)</li> <li>IOT Ready (4 Standard Google intents usable and/or optional 4 additional Android Intents)</li> <li>Build in NFC Technologie</li> </ul>			
Run times**	Use Time in % with typical user profiles Speak / Hear / Standby	High noisy areas with sound level above 100 dB	Loud noisy areas with sound level between 84 and 100 dB	Noisy areas with sound level up to 84 dB
	5 / 5 / 90	-> 47 h	-> 60 h	-> 78 h
	25 / 25 / 50	-> 16 h	-> 27 h	-> 45 h
	50 / 50 / 0	-> 9 h	-> 16 h	->30 h
		Full sound level (8/8)*	Very high sound level (4/8)*	High sound level (2/8)*
	*There are 8 different volume levels possible. **determined runtimes on the Smart-Ex® 01 based on RSM-Ex 01 software version V 16			
Stand-by time	Approx. 80 hours after commissioning via the 3.5mm jack of an Android or Windows device			
Temperature rang				
IP rating	IP 64 following EN/IEC 60079-0 (ATEX/ IECEx) IP 65 / 67 following EN/IEC 60529 (industrial standard)			
Accessories	<ul> <li>Removable belt clip</li> <li>Charging cable</li> <li>Docking station (optional)</li> <li>Connection of additional headsets (optional)</li> </ul>			

